

APC Back-UPS™ 800, 1000

Part Number: BX800L-LM, BX1000L-LM



Battery Backup with Surge Protection for Computers and Electronics

The Back-UPS 800 and 1000 from APC by Schneider Electric protect your computer and electronic equipment from damaging power outages, surges and spikes while providing short term battery power during an outage. The 800 and 1000 feature Automatic Voltage Regulation (AVR), which instantly adjusts high and low voltage fluctuations to safe levels for your electronics, saving battery power for when you need it most during storms and power outages. Equipped with NEMA 5-15R sockets, the BX800L-LM and BX1000L-LM keep your desktop computer, monitor or other critical devices (router, modem, television, etc.) running when the power goes out. Specifically designed to protect electronic equipment in harsh power environments, the Back-UPS 800 and 1000 ensure maximum productivity and work efficiency.



Product Features

- 1 LED Indicator and Audible Alarms
Quickly understand the unit and power status through visual and audible indicators.
- 2 Automatic Voltage Regulation (AVR)
“Boost and Trim” AVR instantly corrects voltage fluctuations without using the battery, allowing you to work indefinitely through inconsistent power, saving battery life for outages.
- 3 4 to 6 NEMA Battery Backup and Surge Protected Sockets
Keep critical electronic equipment running when the power goes out, so you can protect your work and save your data.
- 4 Replaceable Fuse Circuit Breaker
Provides for easy recovery from circuit overloads and protects your UPS and connected electronics from electrical damage.
- 5 Automatic Diagnostic Testing
Periodic battery self-test ensures early detection of a battery that needs to be replaced, ensuring your unit is ready when you need it.
- 6 2 Yr Warranty
APC offers a 2 year warranty with free technical phone and online support, providing customer peace of mind.
- 7 Easy to use “one step” battery connector.



BX800L-LM

BX1000L-LM

Back-UPS BX800L-LM, BX1000L-LM Specifications

Model Number	BX800L-LM	BX1000L-LM
Output		
Output Capacity	800 VA / 400Watts	1000 VA / 600 Watts
Output Voltage / Frequency (On utility)	120V, 55-65Hz +/-1Hz	
Output Voltage / Frequency (On battery)	120V, 60 Hz +/-1 Hz	
Output Connections	4 NEMA 5-15R sockets	6 NEMA 5-15R sockets
Waveform Type	Stepped Approximation to Sine Wave	
Input		
Input Voltage / Frequency	89 -145V 55-65Hz +/-1Hz	89 -145V 55-65Hz +/-1Hz
Input Connection	NEMA power cord	
Surge Protection		
AC Power Surge Protection	All sockets	
Physical		
Unit Dimensions (H x W x D)	142 x 101 x 300 mm	182 x 130 x 320 mm
Unit Weight	4.9 kg	8.2 kg
Shipping Dimensions (H x W x D)	223 x 143 x 347 mm	285 x 197 x 395 mm
Shipping Weight	5.1kg	8.9kg
Color	Black	
UPC Code	731304323198	731304323174
Battery		
Battery Type	Maintenance-free, sealed lead-acid battery, leak proof	
Battery Size	12 volt, 9.Ah	12 volt, 7 Ah (x2)
Management		
Alarms	Visual (LED) and audible alarms	
Conformance		
Warranty	2 years repair or replace (excluding battery) and 1 year for battery	
Regulatory Approvals	cTUVus , FCC Class A	

APC *by Schneider Electric*

132 Fairgrounds Rd
West Kingston, RI 02892
www.apc.com

